

# UPDATING METHOD

## LD550 and LD550B AROKA - DP2258

### 8 cells

Download, clicking onto following link to obtain the last updating method for LD550 counterfeit detector :  
<http://www.reskal.com/category/maj/>

### Warnings ! It exists 2 kinds of LD550 machines

To make the difference between these 2 versions, it is necessary to check the number of detection cells

Open the machine upper cover to count the cells.

A) 6 detection cells onto lower part

Details : 4 white cells (LED) et 2 black cells = old model (before 01 Sept 2015)



LD550 lower part of old model

You have to use following file :

A) ld550 .fa62441.\_2258LED\_C20\_EUR+CHF\_2017-16-02.. 6 cellules.UPL

### B) 8 detection cells on lower part

Detail : 6 black cells and 2 white cells (LED) = new version since 02 sept 2015



LD550 lower part of new model


It will be necessary to use following file (only available on demand, only if there is a black screen after updating) :

**LD550(FA62441 CB)(DP-2258LED\_VC)\_C20(n001)-EUR(007)-CHF(008)-(2017-16-02) 8 cellules .UPL**  
\*\*\*

- 1- Select updating for LD550
- 2- Record files onto your computer. **Be careful, downloaded files are zipped and it will be necessary to unzip them before the beginning of the updating.**
- 3- When file is unzipped, open it by double clic.

There are 4 documents.

- 4- Install « **PL2303\_Prolific\_DriverInstaller\_V130.exe** » clicking 2 times on it and follow the method till the end.
- 5-




- 6- Close the windows, clicking onto « finish »


**End of the first step.**

- 7- Double clic onto « **Multi-Target Programmer\_V3.0.Exe** »

A window opens (document is parametered to proceed to the updating, do not amend anything)




- 8- Clic onto « LoadFile ». New windows opens



9- Select with the scrolling menu, following file :

« LD550(FA62441 CB)(DP-2258LED\_VC)\_C20(n001)-EUR(007)-CHF(008)-(2017-16-02) 8 cellules .UPL»




10- Double click on it. Windows closes. Near « File Size » following number appears : 37834. Updating is ready.

11- Switch off LD550 machine.

12- Connect LD550 to PC with USD cable, and the mini USB onto the LD550 machine.

13- Press « REP/DIR » and « CLR » keys in the same time, and switch on LD550 machine.

Screen will show hypens. Release keys.



14- Click onto « Update Soft ». Progress bar appears and runs. LD550 detector will switch off itself after 100% reached.

Nota : in case the progress bar blocked, change your USB port and click again onto « Update Soft ».

**Updating is ended.**

15- Make a test with new banknotes 5 . 10 and 20 .50euros.



*AfterSales contact : Debiaune David*

*Phone : 33.4.73.51.78.20*

*Mobile : 33.6.50.13.34.46*

*Fax : 33.4.73.51.44.35*

Email : [david.debiaune@safetool.fr](mailto:david.debiaune@safetool.fr) / [sav@safetool.fr](mailto:sav@safetool.fr)

Adress : SAFETOOL SAS - ZI chez cotte - 63650 la Monnerie le Montel - France